

# WAKOL Applicator 90

## Technical Information

### Area of application

Battery-operated tubular bag gun for applying Wakol adhesives in 4,200 ml tubular bags. WAKOL Applicator 90 is equipped with a 200 mm distributor head for holding Wakol Replaceable Nozzle, a quick-charger and two 18 V batteries in a case with stand.

### Special properties

- suitable for 4.200 ml tubular bags
- quick-charger
- Two Bosch Professional GBA 18V 2.0 Ah LI-ION batteries
- Compatible with all Bosch Professional GBA 18V and ProCORE 18V batteries

### Technical data

Delivery:	WAKOL Applicator 90, 200 distributor head, two Bosch Professional GBA 18V 2,0 Ah LI-ION batteries, quick-charger with charging indicator, transport case with stand
Drive:	controllable, 9-stage
Holder:	Aluminium tube for tubular bags, diameter 90 mm
Charging Station:	Bosch Professional GAL 18V-40 Battery charging voltage: 14.4V - 18V, charging current: 4.0 A
Weight:	WAKOL Applicator 90 approx. 5.8 kg, incl. case, distributor head, stand, charger, batteries, approx. 14 kg

### Service

Wear and spare parts must be purchased through the Service Department of INNOTECH Marketing und Konfektion Rot GmbH. Do not perform any unauthorised repairs on the electric drive.

Please observe the following points if the device is to be sent to the Service Department:

- Remove batteries from the device and enclose in package. Do not send any mechanically damaged batteries.
- Remove adhesive tube and if necessary remove any adhesive residue. Do not send stand.
- Enclose a precise description of the fault as well as proof of purchase.

Send the package to the following address:

INNOTECH Marketing und Konfektion Rot GmbH

Schönbornstr. 8b

69242 Rettigheim

Tel. +49 (0)7253-9888-55-30

E-Mail: [service@innotech-rot.de](mailto:service@innotech-rot.de)

[www.innotech-rot.de](http://www.innotech-rot.de)

Packages that are not carriage free will not be accepted.

### Important

Lithium batteries have high power. Only charge the battery in the original charger. Improper chargers or damaged batteries may catch fire. Always store batteries in a clean and dry place. Do not short-circuit batteries.

All electrical parts are only intended for work in dry rooms.

We guarantee the uniform high quality of our products. All data is based on tests and many years of practical experience and refers to standardised conditions. The variety of materials used and the different construction site conditions, which lie beyond our control, preclude any claims based on this data. We therefore recommend making sufficient trials. Accompanying flooring manufacturer's instructions and the current national standards must be observed. We gladly provide technical advice.

The product data sheets can be found in their latest version at [www.wakol.com](http://www.wakol.com).

This Technical Information of 06.11.2023 supersedes all previous versions.